

PRODUCT LISTING DATA SHEET (Active Fire Protection Equipment)

Product designation

Tyco, Model QE90, emergency warning & intercommunication system panel
(Refer to the Technical Specification section of this document for further specific detail)

Supplier

Tyco Fire & Security

47 Gilby Road, MOUNT WAVERLEY, VIC, AUSTRALIA, 3149

Manufacturer

Tyco Safety Products

17 Mary Muller Drive, CHRISTCHURCH, NEW ZEALAND, 8241

Supplier's description

The Tyco, Model QE90, emergency warning & intercommunication system panel is a scalable, discrete switch, multi zone microprocessor based system for emergency (voice) evacuation and emergency phone intercommunication with building wardens. Under non-emergency conditions, the emergency warning system can also be used for the distribution of background music or public address announcements.

This equipment consists of a master panel containing the control keys and status indicators for system functions as well as controls and indicators for the first two evacuation zones. To expand the ECP above the initial two zones, additional eight zone display/keyboard expansion modules are added. The theoretical limit to the number of zones is 256 and is dependant on the rating of the power supply.

Amplifiers are available with ratings of 10W, 25W, 50W, 100W and 200W. Other inputs and outputs available include - FIP inputs (discrete and high level), BGA inputs, WIP (Emergency phone) circuits, GP (General Purpose) inputs, and strobe outputs. A single two wire circuit can be used for a WIP connection and a BGA input. All of these circuits are supervised for short and open circuits. The number and sizes of amplifiers and other inputs and outputs for each zone is fully configurable.

The equipment can be arranged through software driven control functions to support up to 16 remote Secondary Emergency Control Panels (SECP) and / or remote equipment racks. Each communication path and audio path is fully supervised and redundant paths are provided. A number of sub-panels each controlling / displaying only local zones can be networked to one or more global control / display locations.

Interfaces to colour graphics and BMS systems are available.

The Tyco, Model QE90, emergency warning & intercommunication system panel is supplied in one or more 18U, 21U, 28U, or 40U high 19" cabinets.

Conformance criteria and evaluation

The Tyco, Model QE90, emergency warning & intercommunication system panel has been evaluated and verified as conforming with the relevant requirements of the following criteria.

1. Australian Standard AS 2220.1-1989, 'Emergency warning and intercommunication systems in buildings - Equipment design and manufacture'.

Listing is subject to ActivFire Scheme terms and conditions as applicable to the designated registrant and supplier.



This product listing data sheet should be read in conjunction with the general requirements of the terms and conditions of listing under the ActivFire Scheme.

Limitations/conditions of conformance

Limitations/conditions of conformance, where identified on this Product Listing Data Sheet, are derived from qualifications within the report of the testing agency and/or other related technical documentation. It is recommended that all details with respect to design, assembly and installation instructions and restrictions should be checked against the supplier's/manufacturer's current technical manual/data sheets and the requirements of the Authority having Jurisdiction.

Specified limitations/conditions, determined from the evaluation for conformity, include the following.

- i. The WIDG2004 adaptor board where fitted shall carry the Renesas M16C62 microcontroller as the replacement for the Texas Instruments TMS77C82 microcontroller.
- ii. Where the Airphone TSBE RED WIP handset is installed inside the panel, emergency warning & intercommunication system panel, the Sound Pressure Level is required to exceed 80 dB(A) at a distance of one metre and be distinguishable from fault/alarm audible indicator operation.
- iii. When the Altronics Firephone A2095 WIP handset is used in the Emergency Control Panel (ECP), the distinctive audible call sounder shall be provided by the controlling ECP.

Technical specification

The following details are a representative extract of the technical specification for the Tyco, Model QE90, emergency warning & intercommunication system panel and may be subject to change. Complete and current details should be determined from the designated supplier's/manufacturer's technical manual/data sheets.

Power supply/battery chargers:

Model	Power supply	Battery charger	Report
PSU 308	27.28Vdc @ 12 A	27.27 Vdc @ (12.24-Iq) A	F410/R1, Dec. 1991, AS 2220.1-1989 incl. amdt. 1
PSU 2403	27.31 Vdc @ 3 A	27.31 Vdc @ (3.05-Iq) A	
SEPS 9009	27.23 Vdc @ 2 A	27.23 Vdc @ (2.68-Iq) A	
PSU 2406	27.1Vdc @ 6 A	27.1 Vdc @ (6-Iq) A	XF1513/R2, Jan. 2000, AS 2220.1-1989 incl. amdt. 1 & 2.
PSU 2412	27.1Vdc @ 6 A	27.1 Vdc @ (12-Iq) A	

Visible Alert/Evac. EOL: 2k7 Ohms
WIP EOL: 10k Ohms
FIP's/BGA's EOL: 10 V Zener Diode
Speaker EOL: 56k Ohms

Module power consumption

Module	(Iq) Quiescent Current	(Io) Operational
Typical System (MECP)	2.45 A	-
Typical System (SECP)	360 mA	-
ECP 9702	220 mA	8 mA per active led
EMSP 8911	10 mA	8 mA per active led
EMUX 9601	110 mA	-
EAMP 9001	60 mA	0.8 A - 10 W Amplifier 1.8 A - 25 W Amplifier
WIPS 9004	200 mA Plus 2 mA per WIP	-
FIB 8910	28 mA Plus 8 mA per input	-
FIPE 9004	8 mA per input	-
STRM 9502	40 mA per input	30 mA per strobe output plus strobe current
Fluorescent Light	-	0.27 A
PSU 2406	10 mA	-
PSU 2412	10 mA	-
ECM 9603	135 mA @ 9.6 Vdc to 85 mA @ 24 Vdc	-
SPIF9709	10 mA	10 - 80 mA
MWIP9903	80 mA	Plus 14 mA per WIP
AMP200	120 mA	12.4 A
HAMP9308	60 mA	3.1 A / 50 W Amp 6.2 A / 100 W Amp
RING9006	20 mA	
STBT9008	5 mA	
STBM9008	45 mA	Plus strobe current

Module	(Iq) Quiescent Current	(Io) Operational
WIPS2000/WTRM2000	120 mA @ 19 V to 28.5 V	17 mA per WIP in talk mode.

Supplementary information

External devices	Model/part no.	Report
Redford extended range loudspeakers with M1109 multi-tapped transformer	C0626 and C2000 (Note 1)	F410/R1, Dec. 1991, AS 2220.1-1989, incl. amdt. 1
Audio Telex Extended range loudspeaker with ATC 5006R multi-tapped transformer	ATC 5010	
MERRY Electronic microphone	DM-538	
TELEX microphone	NC450D	
University sound microphone	US602FL	
Warden intercom hand set	AIPHONE TB-RC	
Emergency alarm break glass:		
KAC of Alcester (England)	KWB901/SW	
Carters of Burnley (England)	P30	
Visible alarm device:		
KOBISHI 24 V/DC 250 mA strobe light	SL-5	
Warden intercom hand set	Altronic A2095 Fire Phone	XF1378/R1, May-98 AS 2220.1-1989, incl. amdt. 1 & 2.
Warden intercom hand set	Aiphone TBSE RED	XF1511/R1, May 1999 AS 2220.1-1989, incl amdt. 1 & 2

Note 1: Needs 5 terminals on speaker to facilitate coupling capacitor

Evaluated modules

Module	Assembly designation (code/rev.)	PCB designation (code/issue/rev.)	Technical drawing designation/ rev.	Report
Emergency Control Module	PA0661 B/2 PA0663 B/2	ECP 9002 /B	ECP 9002/2 Sht's 1-9	F410/R1, Dec-1991 AS 2220.1- 1989 incl. amdt. 1
8 Zone Expansion Keyboard/ Display Module	PA0653 F/5 PA0659 F/5	EMSP 8911/F	EMSP 8911/5 Sht's 1-2	
Signal Interface Module	PA0857 D/3	SE 9004/D	SE 9004/2 Sht 1	
Tone Generator Multiplexer Module	PA0654 C/8	EMUX 9002/C	EMUX 9002/8 Sht's 1-4	
Audio Amplifier Module (4x10 W or 2x25 W (bridged))	PA0650 E/6	EAMP 9001/E	EAMP 9001/6 Sht's 1-3	
Line Transformer (4 x 10 W)	PA0655 2/3	TRAN 8872-1/2	TRAN 8872-1/3 Sht 1	F410/R1, Dec-1991 AS 2220.1- 1989 incl. amdt. 1
Line Transformer Module (2 x 25 W)	PA0664 2/3	TRAN 8872-2/2	TRAN 8872-2/3 Sht 1	
Fire Alarm/BGA Master Module	PA0851 F/8/2	FIB 8910/EF	FIB 8910/8 Sht's 1-3	
Fire Alarm/BGA Expansion Module	PA0852 C/4	FIPE 9004/C	FIPE 9004/4 Sht 1	
Warden Intercommunications Phone Slave Module	PA0662 E/7	WIPS 9004/E	WIPS 9004/7 Sht's 1-5	
WIP Termination Module	PA0858 C/3	WTRM 9007/C	WTRM 9007/3 Sht 1	
Strobe Driver Module	PA0667 2/4/1	STBM 9008/2	STBM 9008/4 sht's 1-3	
Strobe Termination	PA0668 C/3/3	STBT 9008/C	STBT 9008/3 Sht 1	
Backplane Module	PA0660 A/1	BPLN 2000/A	BPLN 2000/1 Sht 1	XF1834/R1, February 2002, AS 2220-1989, incl. amdt. 1 & 2
Power Supply / Battery Charger	699-156 D/2	699-140/D	699-140/2.2 Sht 1	F410/R1, December 1991 AS 2220-1989, incl. amdt. 1
Siemens Mains Filter (4 Amps)	B84108-K40-A			

Module	Assembly designation (code/rev.)	PCB designation (code/issue/rev.)	Technical drawing designation/ rev.	Report
SECP Power Supply	PA0669 1/2	SEPS 9009/1	SEPS 9009/2 Sht 1	
SECP Power Supply Monitor	PA0666 1/3	EPSM 9007/1	EPSM 9007/3 Sht 1	
Power Supply / Battery Charger	PSU2403	699-160/B	699-160/1 Sht 1	
Power Supply Indicator	PA0678 A/1	699-159/A	699-159/1 Sht 1	
Murata Mains Filter (5 Amps)	PLF-2V-5RA-501			
WIP Master Phone Ring9006	PA 0656 C/3	RING 9006/C	RING 9006/3 Sht 1	
MECP Signal	PA0677 A/2/1	MEXP 9103/A	MEXP 9103/2 Sht 1	
Transformer Module 2 x 50 W zones	PA0691 H	HTRN 9308/B	HTRN9308/4	XB1238/R1, May 1994, AS 2220.1-1989, incl. amdt. 1
Transformer Module 1 x 100 W Zone	PA0692 H	HTRN 9308/B	HTRN9308/4	
High Power Audio Amplifier 2 x 50W / x 100W	PA0690 D/8	HAMP 9308/D	HAMP9308/8 Sht's 1-4	
Strobe Relay Module STRM9502	PA0697 D/4/3	STRM 9502/D	STRM 9502/4 Sht's 1-2	XF1135/R1, Feb. 1996, AS 2220-1989, incl. amdt. 1 & 2.
Secondary Panel Interface Module SPIF9506	PA0699 B/4/2	SPIF 9506/B	SPIF 9506/4 Sht's 1-2	
Secondary Panel Interface Module SPIF9709	PA0849 A/1/3	SPIF 9709/A	SPIF 9709/1	XF1466/R1, Aug. 1999, AS 2220-1989, incl. amdt. 1 & 2.
Emergency Control Panel ECP9702	PA0641 C/5	ECP9702/C	ECP9702/5, Sht's 1 to 9	XF1398/R2, AS 2220.1-1989, incl. amdt. 1 & 2
Emergency Control Panel ECP9702	PA0643 C/5/3	ECP9702/C	ECP9702/5, Sht's 1 to 9	
4 X 25W Line Transformer	PA0791 B/1/2	TRAN 9705-1/B	TRAN 9705-1/1, Sht 1	
4 X 25W Line Transformer with Relays	PA0792 B/1/2	TRAN 9705-2/B	TRAN 9705-2/1, Sht 1	
2 X 25W Line Transformer	PA0793 B/1/2	TRAN 9705-3/B	TRAN 9705-3/1, Sht 1	
2 X 25W Line Transformer with Relays	PA0794 B/1/2	TRAN 9705-4/B	TRAN 9705-4/1, Sht 1	
4 X 10W Line Transformer	PA0795 B/1	TRAN 9706-1/B	TRAN 9706-1/1, Sht 1	
4 X 10W Line Transformer with Relays	PA0796 B/1	TRAN 9706-2/B	TRAN 9706-2/1, Sht 1	
PSU 2406 'brick (ME0330) Monitor / Mains Termination Board	PA0811 C/4	1966-1-1/C	1966-1-1/4 Sht. 1	XF1513/R2, Jan-2000, AS 2220.1-1989, incl. amdt. 1 & 2.
PSU 2406 'rack mounting' (ME0330) Monitor / Mains Termination Board	PA0811 C/4	1966-1-1/C	1966-1-1/4 Sht. 1	
PSU 2412 'rack mounting' (ME0330) Monitor / Mains Termination Board	PA0813 C/4	1966-1-2/C	1966-1-2/4 Sht. 1	
Powerbox Switching PSU	ME0332			
Evacuation	PA0698 B/3/5	ECM 9603/B	ECM 9603/3	XF1273/R2, Jul-2000,

Module	Assembly designation (code/rev.)	PCB designation (code/issue/rev.)	Technical drawing designation/ rev.	Report
Communications Module ECM9603			Sht's 1 to 4	AS 2220.1-1989, incl. amdt. 1 & 2 XF1669/R2, November 2000, AS 4428.0-1998
Evacuation Multiplexer Module EMUX9601	PA0757 C/7/2	EMUX 9601/C	EMUX 9601/7 Sht's 1 to 4	
200W Audio Amplifier AMP200	PA0647 C/2	AMP200/C	AMP200/2 Sht's 1-2	
200W Transformer TRAN200	PA0648 F	TRAN200/A	TRAN200/2 Sht 1	
8 Circuit Warden Intercommunication Phone (WIP) MWIP9903	PA0822 C/3	MWIP9903/C	MWIP9903/3 Sht's 1-4	XF1669/R2, Nov-2000 AS 2220.1-1989, incl. amdt. 1 & 2
WIP Slave Card WIPS2000	PA0642 E/4/2	WIPS2000/E	WIPS2000/4 Sht's 1-4	XF1834/R1, Feb-2002, AS 2220.1-1989, incl. amdt. 1 & 2
WIP Termination Module WTRM2000	PA0922 B/1/2	WTRM2000/B	WTRM2000/1 Sht 1	

System eproms

Module description	Report
ECP-EVAC (SF0107) Site specific V 4.40	F410/R1, Dec-1991, AS 2220.1-1989, incl. amdt. 1.
ECP-WIP Master Generic (SF0177) V 2.14 C\$3743	XL1091/R1, Jan-1996, Compliance Listing Audit
ECP-EVAC with ECM9603 (SF0209) V 3.20 C\$45A3	XL1145/R1, Mar-1998, Compliance Listing Audit
MECP/SECP ECP WIP MASTER V 2.14 (U52)	XF1135/R1, Feb-1996, AS 2220.1-1989 incl. amdt 1 & 2
ECP EVAC V 2.27	XL1145/R1, Mar-1998, Compliance Listing Audit
FIP/BGA Mater Module (SF0127) V2.02 C\$C82D	XF1135/R1, Feb-1996, AS 2220.1-1989 incl. amdt 1 & 2
WIP Slave Module (SF0180) V1.51 C\$14D11A	XL1145/R1, Mar-1998, Compliance Listing Audit
STROBE DRIVER MODULE QE90 SLAVES (SF0120) V 1.49 C\$4BF8	F410/R1, Dec-1991, AS 2220.1-1989, incl. amdt. 1.
EMUX 9601 (SF0130) QE90 EMUX 9601 (U1) V 1.14 C\$75DA	
EMUX Speech (U2) 16 sec Standard V 1.01 EVAC/ALERT S 4843	
PSU2406/2412 (SF0189) U1 Ver. 1.4 1.5 \$2ECE	XF1513/R2, Jan. 2000, AS 2220.1-1989 incl. amdt. 1 & 2.
MWIP (SF0112) U5 V 1.30 SEG. 6201 C\$284F	XF1669/R2, Nov. 2000, AS 2220.1-1989 incl. amdt. 1 & 2.
ECM Module ECM 9603 (SF0136) V5.41 Site Specific	XF1273/R2, Jul-2000, AS 2220.1-1989, incl. amdt. 1 & 2
WIP 2000 Card (SF0233) U1 V1.69 \$B549	XF1834/R1, Feb-2002, AS 2220.1-1989, incl. amdt. 1 & 2

Module description	Report
EMUX9601 (WIDG2004) SF0312 V 1.21 K\$944C (current) V 1.20 K\$5592 (as evaluated)	XF2229/R1, Jan. 2007, AS 2220.1-1989, incl. amdt. 1 & 2
Strobe Master (WIDG2004) SF0313 V 1.7 K\$1412	
FIP/BGA Master (WIDG2004) SF0314 V 2.11 K\$C4F5	
ECP WIP Master (WIDG2004) SF0315 V2.33 K#E7CC	
EPC – EVAC Flash-based (SF0107) V 6.05 K\$3A14 (base)	